

# Certificate

No. **ESY 090313 0054 Rev. 00**

**Holder of Certificate:** **Autarco Group BV**

Torenallee 20  
5617 BC Eindhoven  
THE NETHERLANDS

**Product:**

**Converter**

**Hybrid Inverter**

**Model(s):**

**S2.OH125000(ND), S2.OH125000,  
S2.OH100000(ND), S2.OH100000,  
S2.OH80000(ND), S2.OH80000**

**Parameters:**

See next pages.

**Applicable standards:**

EN 50549-1:2019  
EN 50549-10:2022


This Certificate confirms the compliance with the above listed standards on a voluntary basis. It refers only to the sample submitted to TÜV SÜD Product Service GmbH and does not certify the quality or safety of the serial products. It was issued according to TÜV SÜD Product Service certification program Photovoltaics and Grid Integration. For details see: [www.tuvsud.com/ps-cert](http://www.tuvsud.com/ps-cert)

**Test report no.:**

704092534910-00

**Date,**

2026-02-10



( Zhengdong Ma )

# Certificate

**No. ESY 090313 0054 Rev. 00**

Parameters:

Models	S2.OH80000(ND)	S2.OH80000
PV-Input:		
Max. input voltage	DC 1000 V	
Mppt voltage range	DC 150, ..., 950 V	
Max. input current	DC 10 X 42 A	
Isc PV (absolute maximum)	DC 10 X 60 A	
AC-Output (Grid side):		
Nominal output voltage	3/N/PE AC 230/400 V	
Nominal output frequency	50 Hz	
Max.(Rated) apparent output power	80000 VA	
Max.(Rated) output current	AC 115.5 A	
Power factor range	-0.8, ..., 1, ..., +0.8	
Battery:		
Battery Type	Li-ion	
Battery Voltage Range	DC 300, ..., 950 V	
Max. Charge / Discharge Current	DC 100 A X 2 / 100 A X 2	

Models	S2.OH100000(ND)	S2.OH100000
PV-Input:		
Max. input voltage	DC 1000 V	
Mppt voltage range	DC 150, ..., 950 V	
Max. input current	DC 10 X 42 A	
Isc PV (absolute maximum)	DC 10 X 60 A	
AC-Output (Grid side):		
Nominal output voltage	3/N/PE AC 230/400 V	
Nominal output frequency	50 Hz	
Max. (Rated) apparent output power	100000 VA	
Max. (Rated) output current	AC 144.3 A	
Power factor range	-0.8, ..., 1, ..., +0.8	
Battery:		
Battery Type	Li-ion	
Battery Voltage Range	DC 300, ..., 950 V	
Max. Charge / Discharge Current	DC 100 A X 2 / 100 A X 2	

Models	S2.OH125000(ND)	S2.OH125000
PV-Input:		
Max. input voltage	DC 1000 V	
Mppt voltage range	DC 150, ..., 950 V	
Max. input current	DC 10 X 42 A	

# Certificate

**No. ESY 090313 0054 Rev. 00**

Isc PV (absolute maximum)	DC 10 X 60 A
AC-Output (Grid side):	
Nominal output voltage	3/N/PE AC 230/400 V
Nominal output frequency	50 Hz
Max. (Rated) apparent output power	125000 VA
Max. (Rated) output current	AC 180.4 A
Power factor range	-0.8, ..., 1, ..., +0.8
Battery:	
Battery Type	Li-ion
Battery Voltage Range	DC 300, ..., 950 V
Max. Charge / Discharge Current	DC 100 A X 2 / 100 A X 2

# Certificate

No. **ESY 090313 0054 Rev. 00**

Evaluated protection function and operational capabilities

Clause(s) / subclause(s) of EN 50549-1:2019	Applicable clause(s) / subclause (s) of this document	Remarks, optional modes and constraints	Verdict
4.4.2 Operating frequency range	5.2.1 Frequency operating range	--	Pass
4.4.3 Minimal requirement for active power delivery at underfrequency	5.2.1 Frequency operating range	--	Pass
4.4.4 Continuous operating voltage range	5.2.2 Voltage operating range	--	Pass
4.5.2 Rate of change of frequency (ROCOF) immunity	5.3.1 Immunity to disturbances – Rated of change of frequency (ROCOF)	--	Pass
4.5.3.2 Generating plant with non-synchronous generating technology	5.3.3 Immunity to disturbances - Fault ride through, over-voltage (OVRT) and under-voltage (UVRT)	--	Pass
4.5.4 Over-voltage ride through (OVRT)	5.3.3 Immunity to disturbances - Fault ride through, over-voltage (OVRT) and under-voltage (UVRT)	--	Pass
4.6.1 Power response to overfrequency	5.4 Active response to frequency deviation	--	Pass
4.6.2 Power response to underfrequency	5.4 Active response to frequency deviation	--	Pass
4.7.2.2 Voltage support by reactive power, Capabilities	5.5.1 Power capabilities assessment	--	Pass
4.7.2.3 Voltage support by reactive power, Control modes	5.5.2 Voltage support by reactive power - test to determine the reactive power control modes	Q setp. Q(U) Cos φ setp. Cos φ (P)	Pass
4.7.2.3.2 Set point control modes	5.5.2.3 Verification procedure for set point control	Q setp. Cos φ setp.	Pass
4.7.2.3.3 Voltage related control modes	5.5.2.5 Verification procedure for power related control modes for reactive power	Q(U)	Pass
4.7.2.3.4 Power related control mode	5.5.2.5 Verification procedure for power related control modes for reactive power	Cos φ (P)	Pass
4.7.3 Voltage related active power reduction	5.6 Voltage related active power reduction - P(U)	P(U)	Pass
4.7.4.2.2 Zero current mode for converter connected generating technology	5.3.3 Immunity to disturbances - Fault ride through, over-voltage (OVRT) and under-voltage (UVRT)	--	Pass
4.9.3 Requirements on voltage and frequency protection	5.8.3 Verification procedure for generating plants to be connected to a LV distribution network with Interface protection as internal device	--	Pass
4.9.4 Means to detect island situation	5.8.6 Islanding detection	Active methods tested with a resonant circuit	Pass

# Certificate

No. **ESY 090313 0054 Rev. 00**

		according to EN 62116	
4.10.2 Automatic reconnection after tripping	5.9.3 Automatic reconnection after tripping	--	Pass
4.10.3 Starting to generate electrical power	5.9.4 Starting to generate electrical power	--	Pass
4.11.1 Ceasing active power	5.10 Active power reduction on set point	--	Pass
4.11.2 Reduction of active power on set point	5.10 Active power reduction on set point	--	Pass
4.12 Remote information exchange	5.11 Remote information exchange	Standardized communication protocol not provided by manufacturer	N/A
4.13 single fault tolerance of interface protection system and interface switch	5.12 Requirements regarding single fault tolerance of interface protection system and interface switch	--	Pass

# Certificate

No. **ESY 090313 0054 Rev. 00**

Evaluated parameter and parameter range

Name of parameter set		EN50549			
Specific technical requirement (e.g. grid codes)		EN 50549-1:2019			
Clause(s) / subclause(s) of EN 50549-1:2019	Parameter	Remarks/ additional information	Configurable value range	Default value	
4.4.2 Operating frequency range	47.0 – 47.5 Hz Duration	--	0 – 20 s	Unlimited with protection setting only	
	47.5 – 48.5 Hz Duration	--	30 – 90 min	Unlimited with protection setting only	
	48.5 – 49.0 Hz Duration	--	30 – 90 min	Unlimited	
	49.0 – 51.0 Hz Duration	--	not configurable	Unlimited	
	51.0 – 51.5 Hz Duration	--	30 – 90 min	Unlimited with protection setting only	
	51.5 – 52 Hz Duration	--	0 – 15 min	Unlimited with protection setting only	
4.4.3 Minimal requirement for active power delivery at underfrequency	Reduction threshold	--	not configurable	No reduction	
	Maximum reduction rate	--	not configurable	N/A	
4.4.4 Continuous operating voltage range	Upper limit	--	not configurable	110% Un	
	Lower limit	--	not configurable	85% Un	
4.5.2 Rate of change of frequency (ROCOF) immunity	ROCOF withstand capability (defined with a sliding measurement window of 500 ms)	--	not configurable	2 Hz/s	
4.5.3.2 Under-voltage ride through (UVRT) Generating plant with non-synchronous generating technology	Maximum power resumption time	--	not configurable	1 s	
	Voltage-Time-Diagram	--	See figure 6 default requirement curve of EN 50549-1:2019	Time [s]	U [p.u.]
				0.0	0.2
				0.15	0.2
			1.5	0.85	
4.5.4 Over-voltage ride through (OVRT)	Voltage-Time-Diagram	--	not configurable See figure 8 of EN 50549-1:2019	Time [s]	U [p.u.]
				0.0	1.25
				0.1	1.25
				0.1	1.20
				5.0	1.20
				5.0	1.15
				60	1.15
			60	1.10	
4.6.1 Power response to overfrequency	Threshold frequency f1	--	50.2 Hz – 52 Hz	50.2 Hz	
	Droop	--	2 % – 12 %	5 %	

# Certificate

No. ESY 090313 0054 Rev. 00

	Power reference	--	PM   Pmax	Pmax
	Intentional delay	--	0 – 2 s	0s
	Deactivation threshold fstop	--	50.0 Hz – f1	deactivated
	Deactivation time tstop	--	0 – 600 s	-
	Acceptance of staged disconnection	--	yes   no	No
4.6.2 Power response to underfrequency	Threshold frequency f1	--	49.8 Hz – 46 Hz	49.8 Hz
	Droop	--	2 – 12 %	5 %
	Power reference	--	PM   Pmax	Pmax
	Intentional delay	--	0 – 2 s	0 s
4.7.2.2 Voltage support by reactive power - Capabilities	Active factor / Reactive power (%Pd) range overexcited	--	0.8 – 1 / 66.67 % P <sub>D</sub> – 0	0.8 – 1 / 66.67 % P <sub>D</sub> – 0
	Active factor / Reactive power (%Pd) range underexcited	--	0.8 – 1 / 66.67 % P <sub>D</sub> – 0	0.8 – 1 / 66.67 % P <sub>D</sub> – 0
4.7.2.3 Voltage support by reactive power - Control modes	Enabled control mode	--	Q setp. Q(U) Cos φ setp. Cos φ (P)	Cos φ setp.
4.7.2.3.2 Voltage support by reactive power - Setpoint control modes	Q setpoint and excitation	--	0 – 66.67 % P <sub>D</sub>	0
	cos φ setpoint and excitation	--	1 – 0.8	1
4.7.2.3.3 Voltage support by reactive power - Voltage related control modes	Characteristic curve – Q (U)	--	--	Indicate default characteristic
	Point a	--	50%Un – 100%Un	93 %Un
	Point b	--	50%Un – 100%Un	94 %Un
	Point c	--	100%Un – 120%Un	106%Un
	Point d	--	100%Un – 120%Un	108 %Un
	Min. reactive power	--	0 – 66.67 % P <sub>D</sub> (Q <sub>max under</sub> )	66.67 % P <sub>D</sub>
	Max. reactive power	--	0 – 66.67 % P <sub>D</sub> (Q <sub>max over</sub> )	66.67 % P <sub>D</sub>
	Time constant	--	3 s – 60 s	3.0 s
	Min cos φ	--	0.0 – 1	0.4
	Lock in power	--	0 % – 20 %	20%
	Lock out power	--	0 % – 20 %	5%
4.7.2.3.4 Voltage support by reactive power - Power related control mode	Characteristic curve – Cos φ (P)	--	--	Indicate default characteristic
	Point a	--	0 – 100%Pn/ PF:-0.8, ..., +0.8	15%Pn/ PF=0.8
	Point b	--	0 – 100%Pn/ PF:-0.8, ..., +0.8	20%Pn/ PF=1
	Point c	--	0 – 100%Pn/ PF:-0.8, ..., +0.8	80%Pn/ PF=1
	Point d	--	0 – 100%Pn/ PF:-0.8, ..., +0.8	90%Pn/ PF=-0.8
	Cos φ	--	0.8 – 1	0.8

# Certificate

No. ESY 090313 0054 Rev. 00

	Time constant	--	3 s – 60 s	3.33 s
	Lock in voltage	--	105 %Un	deactivated
	Lock out voltage	--	100 %Un	deactivated
4.7.3 Voltage related active power reduction	Characteristic curve - P (U)	--	--	Indicate default characteristic
	Point a	--	0 – 100%Pn/ U:0 V, ...,264.5 V	100%Pn/ U=207 V
	Point b	--	0 – 100%Pn/ U:0 V, ...,264.5 V	100%Pn/ U=230 V
	Point c	--	0 – 100%Pn/ U:0 V, ...,264.5 V	100%Pn/ U=253 V
	Point d	--	0 – 100%Pn/ U:0 V, ...,264.5 V	0%Pn/ U=264.5 V
4.7.4.2.2 Zero current mode for converter connected generating technology	Time constant	--	3 s – 60 s	3.33 s
	Enabling	--	enable   disable	disabled
	Static voltage range overvoltage	--	100 %Un – 120 %Un	120 %Un
4.9.3 Requirements on voltage and frequency protection	Static voltage range undervoltage	--	20 %Un – 100 %Un	50 %Un
	Threshold for protection as dedicated device [in A or kW. kVA]	--	16 A – 250 kVA	Not specified, inverter integrated as default
	Undervoltage threshold stage 1	--	0.2 Un – 1 Un	0.85Un
	Undervoltage operate time stage 1	--	0.1 s – 100 s	100 s
	Undervoltage threshold stage 2	--	0.2 Un – 1 Un	0.5Un
	Undervoltage operate time stage 2	--	0.1 s – 5 s	5 s
	Overvoltage threshold stage 1	--	1.0 Un – 1.2 Un	1.2Un
	Overvoltage operate time stage 1	--	0.1 s – 100 s	100 s
	Overvoltage threshold stage 2	--	1.0 Un – 1.3 Un	1.3Un
	Overvoltage operate time stage 2	--	0.1 s – 5 s	5 s
	Overvoltage threshold 10 min mean protection	--	1.0 Un – 1.15 Un	1.1Un
	Underfrequency threshold stage 1	--	47.0 Hz– 50.0 Hz	47.5 Hz
	Underfrequency operate time	--	0.1 s – 100 s	100 s

# Certificate

No. **ESY 090313 0054 Rev. 00**

	stage 1			
	Underfrequency threshold stage 2	--	47.0 Hz – 50.0 Hz	47 Hz
	Underfrequency operate time stage 2	--	0.1 s – 5 s	5 s
	Overfrequency threshold stage 1	--	50.0 Hz – 52.0 Hz	51.5Hz
	Overfrequency operate time stage 1	--	0.1 s – 100 s	100 s
	Overfrequency threshold stage 2	--	50.0 Hz – 52.0 Hz	52Hz
	Overfrequency operate time stage 2	--	0.1 s – 5 s	5 s
	ROCOF protection	--	--	2.5 Hz/s
	ROCOF operate time	--	0 - 1 s	0.5 s
4.10.2 Automatic reconnection after tripping	Lower frequency	--	47.0 Hz – 50.0 Hz	49.5 Hz
	Upper frequency	--	50.0 Hz – 52.0 Hz	50.2 Hz
	Lower voltage	--	50 %Un – 100 %Un	85 %Un
	Upper voltage	--	100 %Un – 120 %Un	110 %Un
	Observation time	--	10 s – 600 s	60 s
	Active power increase gradient	--	5% – 3000%/min	10 %/min
4.10.3 Starting to generate electrical power	Lower frequency	--	47.0 Hz – 50.0 Hz	49.5 Hz
	Upper frequency	--	50.0 Hz – 52.0 Hz	50.1 Hz
	Lower voltage	--	50 %Un – 100 %Un	85 %Un
	Upper voltage	--	100 %Un – 120 %Un	110 %Un
	Observation time	--	10 s – 600 s	60 s
	Active power increase gradient	--	5% – 3000 %/min	disabled
4.11.1 Ceasing active power	Activation option	--	Can be achieved by APP or Autarco cloud, acceptance should be made by the DSO and responsible party	
4.11.2 Reduction of active power on set point	Activation option	--	Can be achieved by APP or Autarco cloud, acceptance should be made by the DSO and responsible party	
4.12 Remote information exchange	Available communication standards	--	Standardized communication protocol not provided by manufacturer	